

AXIS T91R61

For tilting of Axis network radar detectors

AXIS T91R61 Wall Mount enables flexible mounting and tilting of Axis network radar detectors. The adjustable arm can be tilted up to 90 degrees for optimal vertical angle of detection. Made of powder-coated aluminum with IK08-, and NEMA 250 Type 4X-rating makes AXIS T91R61 robust and weather resistant. AXIS T91R61 includes one AXIS T94R01P Conduit Back Box for use of cable protection products and is compatible with 3/4" conduits, M25 cable protection products and the Axis Conduit Interface (ACI) adapter range.

- > **Compatible with Axis network radar detectors**
- > **90 degrees tilting angle**
- > **Protection against water and dust**
- > **Easy to install**



AXIS T91R61

General		Approvals
Supported products	AXIS D2050-VE Network Radar Detector	IEC 60068-2-1, IEC 60068-2-2, IEC 60068-2-6, IEC 60068-2-14, IEC 60068-2-27, IEC 60068-2-78, IEC/EN 62262 IK08, NEMA 250 Type 4X
Casing	Powder coated, Chromate aluminum Color: white NCS S 1002-B Stainless steel screws	Included accessories Installation Guide AXIS T94R01P Conduit Back Box
Dimensions	147 x 80 x 120 mm (5 3/4 x 3 1/8 x 4 3/4 in)	Optional accessories AXIS T91B47 Pole Mount AXIS T94R01B Corner Bracket For more accessories, see axis.com
Weight	0.9 kg (2 lb)	Warranty 3-year warranty, see axis.com/warranty
Maximum load	5 kg (11 lb)	Environmental responsibility: axis.com/environmental-responsibility
Cable routing	Back: Cable hole Side: Cable conduit holes M20 (3/4")	
Environment	Indoor Outdoor	