

DH-PFR5QI-E60-PV

4MP IR 60 m Sound & Light Visual Radar



System Overview

Equipped with a 60 GHz radar chip and a 4MP wide-angle lens, the visual radar realizes all-weather and high-precision detection. The visual radar supports speed filtering, automatic calibration, changing live view protection zone into radar protection zone. With the intelligent algorithm, the visual radar achieves extremely low rate of false alarms and no missing alarms, which greatly improves the video quality in severe environment. The visual radar supports alarm linkage with sound and light, and integrates radar detection and video playback.

Functions

60 GHz Radar & 4MP Video Integration

The Self-developed Dahua 60 GHz radar algorithm combines high-quality video display, improving perimeter/area intrusion protection and realizing wide-range, 7/24 all-weather and high-precision detection.

One-click Calibration

Dahua intelligent algorithm realizes one-click auto/manual calibration which is easy to operate and applicable to various scenes.

Multi-level Perimeter Protection

Support region setting with different alarm priority, external alarm linkage, human and vehicle filtering, vehicle detection with low and medium speed, and intrusion/tripwire rules.

- · Radar and video integration.
- 60 GHz high frequency radar is not affected by severe weather.
 Extremely low rate of false alarms and no missing alarms.
- 4MP 1/1.8" CMOS image sensor, low illuminance, high image definition.
- Easy to calibrate: One-click auto calibration and manul calibration.
- Supports drawing protection zone on live view which can be transformed to radar protection zone automatically; applicable to various scenes.
- · Target filtering of human and vehicles.
- Speed filtering of target with a speed of 0–40 km/h, achieving accurate and efficient detection.
- Outputs max. 4MP (2560 × 1440) @30 fps.
- H.265 codec, high compression rate, ultra-low bit rate.
- Built-in IR illuminator, and the max. illumination distance is 35 m.
- Built-in warning white light and speaker links alarm to performs sound and light alarm.



Intelligent Algorithm of Radar

Intelligent algorithm is used to identify complex scenes and achieve high accuracy in different scenarios. Support human and vehicle recognition and speed filtering of moving targets.

Smart H.265+ & Smart H.264+

With advanced scene-adaptive rate control algorithm, Dahua smart encoding technology realizes higher encoding efficiency than H.265 and H.264, provides high-quality video, and reduces the cost of storage and transmission.

Protection and Certifications

Meet IP66 and CE RED standards.

Scene

Applicable to various perimeter intrusion scenes, such as villa, warehouse, prison and parking lot. It provides a safer and more comprehensive solution for protection.



Technical Specification			50 Hz: 25 fps (704 × 576); 25 fps (352 × 288)
Radar			60 Hz: 30 fps (704 × 480); 30 fps (352 × 240) Third stream:
Max. Target Number	64		50 Hz: 25 fps (1920 × 1080); 25 fps (1280 × 960); 25 fps (1280 × 720) 60 Hz: 30 fps (1920 × 1080); 30 fps (1280 × 960);
Distance	60 m (196.85 ft)		30 fps (1280 × 720)
Angle	Horizontal: 120° Pitch angle: 26°	Video Bit Rate	H.264: 3 Kbps-8192 Kbps; H.265: 3 Kbps-8192 Kbps
Distance Accuracy	±0.5 m (1.64 ft)	Day/Night	Color/B/W
Angle Accuracy	±1°	BLC	Yes
Max. Detection Speed	43.2 km/h, continuous trace	HLC	Yes
Min. Detection Speed	0.72 km/h, continuous trace	WDR	102 dB
Modulation Method	FMCW	White Balance	Auto/manual/natural/street lamp/outdoor
Scan Frequency	20 Hz	Gain Control	Auto/manual
Working Frequency	60 GHz-61 GHz	Noise Reduction	2D NR/3D NR
Supported Target Type	Human; vehicle	Default Bit Rate with Default Resolution	6144 Kbps (2560 × 1440)
Transmission Power	< 20 dBm (100mW)	Defog	Yes
Camera		Image Stabilization	Yes
Image Sensor	1/1.8" CMOS	LDC	Yes
Pixel	4MP	Alarm	
Max. Resolution	2560 (H) × 1440 (V)	Alarm Event	Network disconnection; IP conflict; illegal access; intrusion; tripwire
Electronic Shutter Speed	1/3 s-1/100000 s	Alarm Input	3
Min. Illumination	0.0036 Lux @F1.6 (Color); 0.0036 Lux @F1.6 (B/W); 0 Lux (IR on)	Alarm Output	2, support alarm linkage
S/N Ratio	> 56 dB	Alarm Linkage	Snapshot/SD card recording/email
Illumination Distance	35 m (114.83 ft) (0°, visible human body shape)	Network	
Illuminator Number	4	Network Port	1 (RJ-45; support 10 M/100 M network data)
Lens		NetworkTore	IPv4/IPv6; HTTP; HTTPS; SSL; TCP/IP; UDP; UPnP;
Lens Type	Fixed-focal	Network Protocol	ICMP; IGMP; SNMP; RTSP; RTP; SMTP; NTP; DHCP; DNS; PPPOE; DDNS; FTP; IP Filter; QoS; Bonjour; 802.1x
Lens Mount	M16	Interoperability	ONVIF (Profile S); CGI; Imou
Focal Length	2.8 mm (equivalent focal distance of 1/2.7")	Storage	NAS; FTP; Micro SD card (128 G)
Max. Aperture	F1.6	Storage	IE 7 and later
Field of View Iris Control	Horizontal: 104°; Vertical: 55°; Diagonal: 121° Fixed	Browser	Chrome 45 and earlier Firefox 46 and earlier
Close Focus Distance	0.2 m	User/Host	20 (total bandwidth: 64 M)
Video		SDK and API	Yes
Video Compression	H.265; H.264; H.264H; H.264B	Management Software	DSS
Smart Codec	H.264/H.265	Sound and Light Alarm	
	Main stream: 50 Hz: 25 fps (2560 × 1440); 25 fps (2048 × 1536); 25 fps (1920 × 1080); 25 fps (1280 × 960); 25 fps (1280 × 720) 60 Hz: 30 fps (2560 × 1440); 30 fps (2048 × 1536);	Number of Warning Light	2
		Warning Light Mode	Yes, flashing mode, solid on mode
Video Frame Rate		Warning Light Delay	Yes, 5 s–30 s
Video Frame Rate	60 Hz: 30 fps (2560 × 1440); 30 fps (2048 × 1536); 30 fps (1920 × 1080); 30 fps (1280 × 960); 30 fps	Warning Light Delay	165, 3 5-30 5

	`			
Warning Speaker Mode	1–3 times			
Alarm Audio Upload & Record	Yes, up to 10 audios			
Alarm Audio Import & Output	Yes			
Function				
Image Setting	Brightness; Contrast; Sharpness; Saturation; Gamma			
OSD Overlay	Time; channel; location; custom			
Record Mode	Manual record; scheduled record; alarm record; Record priority: Manual > external > schedule			
Default	Support one-click restoring			
User Management	Up to 20			
Security	Username and password; MAC address; HTTPS; IEEI 802.1x; network access control			
Region Management	Pre-warning zone; alarm zone; shield zone			
Target Filtering	Yes, human/vehicle			
Speed Filtering	Yes, 0–40 km/h (Objects whose speeds are not within the target speed range will not trigger alarms)			
Recognition Sensitivity	Yes, human, vehicle recognition sensitivity configurable			
Radar Structuring	Yes, target track displayed on live view, including distance, angle, speed and type			
Radar OSD Detection Overlay	Yes, 8 positions			
Device Attitude	Yes, display pitch angle and roll angle			
Protection Zone Mapping	Yes, draw on live view to define actual radar protection zone			
Auto Calibration	Yes, automatically calibrate radar and image			
Manual Calibration	Yes, manually calibrate radar and image			
Sound and Light Linkage	Yes			
Power				
Operating Voltage	12V DC (±30%); PoE (802.3at)			
Power Supply	12V DC/POE			
Power Consumption	Basic power consumption: 10W; Max. power consumption: 22W			
Port	Terminal block			
Port				
SD Card	Yes			
Indicator Light	Yes. Network indicator (yellow); operation indicator (red and green); power indicator (green)			
Audio Input	1 × 3.5 mm port			
Audio Output	1 × 3.5 mm port			
RS-485	1 (baud rate range: 1200 bps–115200 bps)			
Environment				
Operating Temperature	-40°C to +70°C (-40°F to +158°F)			
0	. 050/			

≤ 95%

IP66

Operating Humidity

Protection

Casing	Metal + plastic
Product Dimensions	160.0 mm × 194.4 mm × 210.0 mm (6.30" × 7.65" × 8.27") (L × W × H)
Packaging Dimensions	277.0 mm × 274.0 mm × 224.0 mm (10.91" × 10.79" × 8.82") (L × W × H)
Packaging Method	4 in one package
Net Weight	2.51 kg (5.53 lb)
Gross Weight	3.10 kg (6.83 lb)
Installation	Pole mount; wall mount
Bracket	PFA154
Power Adapter	Optional

Certifications

Ordering Information				
Туре	Model	Description		
Visual Radar	DH-PFR5QI-E60-PV	4MP IR 60 m Sound & Light Visual Radar		
Accessory	PFA154	Pole mount bracket		

Accessory



PFA154 Pole mount bracket

Wall Mount	Pole Mount

Dimensions (mm [inch])

